privest.®

FU9010

# Privest Wireless Alarm Control Panel, DE

The Privest wireless alarm system combines an elegant timeless design with user–friendly operability. With its 33 zones (32 wireless and 1 wired) and its four programmable outputs, the alarm control panel is the heart of the good feeling of security.
The innovative AM radio technology operates on a special frequency within the 868 MHz band that is reserved for wireless alarm systems. Programming and operation are easy thanks to the speech–supported menu navigation (German).
If an event occurs, residents are warned of dangers such as fire, water and burglaries or they are alarmed in case of an emergency via the integrated Piezo signalling device. In addition, an emergency call center or a mobile telephone can be contacted via an integrated speech dialling unit (AWAG). This makes the Privest wireless alarm system the perfect entry–level model among professional alarm systems.

**Product highlights:**

- 868 MHz wireless alarm center AM
- 32 wireless detectors and one wired zone
- Wide coverage
- Small dimensions
- Easy self–installation

© 2012 ABUS Security–Center GmbH & Co. KG, Errors and omissions excepted.

privest.®

FU9010

# Privest Wireless Alarm Control Panel, DE

| Technical Data | |
|---|---|
| Radio frequency | 868.65 MHz AM |
| Voltage | 230 VAC |
| Emergency power supply | 6 x 1.2 V NiCd batteries or 6 x 1.5 V AA alkali |
| Alarm zones | 32 wireless zones / 1 wired zone |
| Alarm outputs | 4 switching outputs + a signal generator output |
| Number of users | 34 |
| Speaker | Integrated for alarm and AWAG function |
| Microphone | Integrated |
| Telephone connection | Analog (PSTN) |
| Event storage | 256 |
| Dimensions (HxWxD) | 196 x 240 x 45 mm |
| Weight | 940 g (incl. batteries) |
| Material | ABS |
| Display | Monochrome, 2–line |
| Language | German |

© 2012 ABUS Security–Center GmbH & Co. KG, Errors and omissions excepted.